

High Frequency Mobile X-ray Camera



Without Battery



With Battery

★ Specifications ★ [GMD100]

- ◇ Power Output: 2.5KW
- ◇ Frequency: 25KHz
- ◇ X-ray Tube: Fixed anode
Focus 2.6(X-ray tube for high frequency)
- ◇ Tube Voltage: 40~100KV (interval 1KV)
40~49KV 50mA 1~160 mAs
50~59KV 42mA 1~160 mAs
- ◇ Tube Current: 60~69KV 36mA 1~140 mAs
70~79KV 31mA 1~125 mAs
80~89KV 28mA 1~100 mAs
90~100KV 25mA 1~80 mAs
- ◇ mAs: 1.0~160 mAs (45steps)
- ◇ Power Supply: 220V ± 10% 50Hz inner-resistance ≤ 1.0Ω
- ◇ Operation Method: Wire/Wireless control

★ Specifications ★ [GMD101A]

- ◇ Power Output: 3.5KW
- ◇ Frequency: 40KHz
- ◇ X-ray Tube: Fixed anode
Focus: 1.5 (X-ray tube for high frequency)
- ◇ Tube Voltage: 40~110KV (interval 1KV)
- ◇ Tube Current: 40~49KV 63mA 1~125mAs
50~59KV 56mA 1~110mAs
60~69KV 45mA 1~90mAs
70~79KV 40mA 1~80mAs
80~89KV 36mA 1~71mAs
90~99KV 32mA 1~63mAs
100~110KV 20mA 1~40mAs
- ◇ mAs: 1.0~125mAs(43 steps)
- ◇ Power Supply: 220V ± 10% 50Hz inner-resistance ≤ 1.0Ω
- ◇ Operation Method: Wire / wireless control
- ◇ GMD101B : GMD101A + Back-up battery

★ Specifications ★ [GMD101C]

- ◇ Power Output: 5.0KW
- ◇ Frequency: 40KHz
- ◇ X-ray Tube: Fixed anode
Focus 1.5mm
- ◇ Tube Voltage: 40~110KV (interval 1KV)
- ◇ Tube Current: 40~49KV 100mA 1~180 mAs
50~59KV 77mA 1~140 mAs
60~69KV 64mA 1~125 mAs
70~79KV 55mA 1~110 mAs
80~89KV 49mA 1~100 mAs
90~99KV 44mA 1~90 mAs
100~110KV 32mA 1~80 mAs
- ◇ mAs: 1.0~125 mAs(43 steps)
- ◇ Power Supply: 220V ± 10% 50Hz inner-resistance ≤ 1.0Ω
- ◇ Operation Method: Wire/Wireless control
- ◇ GMD101D : GMD101C + Back-up battery and rotary pillar